

APPLICATION FOR UNITED STATES PATENT

VOLTAGE CONTROLLED OSCILLATOR

By Inventors:

Beomsup Kim
811 Candlewood Dr.
Cupertino, CA 95125
A Citizen of Korea

Assignee: Berkana Wireless, Inc.

VAN PELT AND YI, LLP
4906 El Camino Real Suite 205
Los Altos, CA 94022
Telephone (650) 903-3500

VOLTAGE CONTROLLED OSCILLATOR

CROSS REFERENCE TO RELATED APPLICATIONS

This application is related to co-pending U.S. Patent Application No.

_____ (Attorney Docket No. BERKP007) entitled PHASE SYNCHRONOUS
5 MULTIPLE TANK OSCILLATOR filed concurrently herewith, which is incorporated
herein by reference for all purposes.

FIELD OF THE INVENTION

The present invention relates generally to Voltage controlled oscillators (VCO's).
A VCO with enhanced Q and better signal to noise ration (SNR) is disclosed.

BACKGROUND OF THE INVENTION

10 Voltage Controlled Oscillators (VCO's) are important components in wireless
communication systems. Figure 1 is a block diagram illustrating a conventional
differential cascaded VCO with an LC tank. The output of stage 102 is input to stage 104
and the output of stage 104 is input to stage 106. The output of stage 106 is negatively
15 fed forward to the input of stage 102 with the positive output being fed into the negative
input and the negative output being fed into the positive input. The cascaded stages
produce a filtering effect with somewhat improved phase noise, but the circuit tends to
consume a large amount of current.

SUMMARY OF THE INVENTION

An improved cascaded VCO is disclosed. In one embodiment, each oscillator stage receives an additional input from a second stage in addition to the conventional input received from a previous stage. The inputs are selected with a phase relationship
5 that causes the total input signal power to each stage to be increased.

It should be appreciated that the present invention can be implemented in numerous ways, including as a process, an apparatus, a system, a device, a method, or a computer readable medium such as a computer readable storage medium or a computer network wherein program instructions are sent over optical or electronic communication
10 links. Several inventive embodiments of the present invention are described below.

In one embodiment, a cascaded voltage controlled oscillator includes a first oscillator stage having a first oscillator stage first input, a first oscillator stage second input and a first oscillator stage output. A second oscillator stage includes a second oscillator stage input and a second oscillator stage output wherein the first oscillator stage
15 output is input to the second oscillator stage input and wherein the second oscillator stage output is fed back to the first oscillator stage second input. A third oscillator stage includes a third oscillator stage input and a third oscillator stage output wherein the second oscillator stage output is fed to the third oscillator stage input.

These and other features and advantages of the present invention will be presented
20 in more detail in the following detailed description and the accompanying figures which illustrate by way of example the principles of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be readily understood by the following detailed description in conjunction with the accompanying drawings, wherein like reference numerals designate like structural elements, and in which:

5 Figure 1 is a block diagram illustrating a conventional differential cascaded VCO with an LC tank.

Figure 2 is a block diagram illustrating a multiple input cascaded LC tank VCO.

Figure 3 is a block diagram illustrating a two input LC tank oscillator used in one embodiment.

10 Figure 4 is a block diagram illustrating a cascaded LC tank oscillator wherein a second input is obtained for each stage by feeding forward the input from a previous stage.

Figure 5 is a block diagram illustrating an improved oscillator stage for use in the cascaded LC tank oscillator shown in Figure 4.

DETAILED DESCRIPTION

A detailed description of a preferred embodiment of the invention is provided below. While the invention is described in conjunction with that preferred embodiment, it should be understood that the invention is not limited to any one embodiment. On the contrary, the scope of the invention is limited only by the appended claims and the invention encompasses numerous alternatives, modifications and equivalents. For the purpose of example, numerous specific details are set forth in the following description in order to provide a thorough understanding of the present invention. The present invention may be practiced according to the claims without some or all of these specific details. For the purpose of clarity, technical material that is known in the technical fields related to the invention has not been described in detail so that the present invention is not unnecessarily obscured.

Figure 2 is a block diagram illustrating a multiple input cascaded LC tank VCO. LC tank oscillators are shown in the illustrated embodiment and are referred to extensively herein. In other embodiments, other types of oscillators are used and are connected in a similar manner as shown. In addition, it should be noted that each LC tank oscillator may be single ended. In the example shown, LC tank oscillators with two inputs are shown.

★ Oscillator stage 204 receives input from stage 202 in a manner similar to that described above. In addition, oscillator stage 204 also receives as an additional input the output signal from oscillator stage 206 which is positively fed back to oscillator stage

204. Similarly, oscillator stage 206 receives input fed forward from stage 204 and fed back positively from stage 208. The output of stage 208 is fed forward negatively to stage 202 with the positive output being input to the negative input and the negative output being input to the positive input. Stage 202 also receives input from the output of stage 204, which is fed back positively. The 45 degree phase difference between the two input signals to each stage of the four stage amplifier causes the input power to be increased and enhances the amplitude of the output. An advantage of this phase arrangement is that the 45 degree added signal tends grow faster than the orthogonally added noise that is introduced, which enhances the SNR.

In other embodiments, different arrangements of the input and output connections are used. In some embodiments, the second input is obtained from a stage that is not immediately next to the stage that is receiving the input, i.e. stages may be skipped. In addition, different numbers of stages are used in other embodiments. The phase relationship among the inputs is arranged so that the input power is increased.

Figure 3 is a block diagram illustrating a two input LC tank oscillator used in one embodiment. Oscillator 300 includes positive input nodes 302 and 304 and negative input nodes 312 and 314. The output is taken at output nodes 322 and 324. Advantageously, NMOS transistors are used at the input nodes to increase ramp up speed.

Figure 4 is a block diagram illustrating a cascaded LC tank oscillator wherein a second input is obtained for each stage by feeding forward the input from a previous

stage. Then inputs for stage 404 are obtained from the output of stage 402 and the fed forward input of stage 402. The inputs for stages 406 and 408 are obtained in similar fashion and the inputs for stage 402 are obtained by negatively feeding forward the output of stage 408 and also negatively feeding forward the input from stage 408. The feed forward relationship increases the ramp up rate of the signal.

Figure 5 is a block diagram illustrating an improved oscillator stage for use in the cascaded LC tank oscillator shown in Figure 4. Oscillator stage 500 includes positive input nodes 502 and 504 and negative input nodes 512 and 514. The input from the immediately previous stage is applied across nodes 502 and 512 and the input from one stage before the immediately previous stage is applied across nodes 504 and 514. A combination of NMOS and PMOS devices are used. In general, PMOS devices tend be slower than NMOS. In the design shown, the PMOS devices receive the signal before the NMOS devices and can be slower. Therefore, smaller size PMOS devices (as small as the NMOS devices) can be used. Thus, power consumption is reduced.

An improved cascaded VCO has been described. Each oscillator stage receives an additional input from a second stage in addition to the conventional input received from a previous stage. The inputs are selected with a phase relationship that causes the total input signal power to each stage to be increased. In addition, improved LC tank oscillators have been disclosed for use in such cascaded VCO architectures.

Although the foregoing invention has been described in some detail for purposes of clarity of understanding, it will be apparent that certain changes and modifications may

be practiced within the scope of the appended claims. It should be noted that there are many alternative ways of implementing both the process and apparatus of the present invention. Accordingly, the present embodiments are to be considered as illustrative and not restrictive, and the invention is not to be limited to the details given herein, but may

5 be modified within the scope and equivalents of the appended claims.

WHAT IS CLAIMED IS:

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995